

# EPSi1000



**silenced INVERTER generating sets with HONDA air-cooled petrol engine, 50Hz, 4 stroke**

## **Generator:**

kVA max.:	1
kVA cont.:	0.9
Amps cont.:	4A at 1~230V
Dimensions l x w x h:	47 x 27 x 38 cm
Dry weight:	14 kg

## **Engine:**

### **Brand/Type:**

**Honda GXH50**

HP:	2.1
Power:	1.6 kW (4100/5800 rpm), 1-cylinder Unleaded gasoline, Air-Cooled
Displacement:	49 cm <sup>3</sup>
Consumption @75% load:	0.47 litres/hour
Tank:	3.8 litres
Autonomy @75% load:	8 hours
Noise level:	64 dB(A)@7m = Lwa 89

## **Alternator:**

### **Brand/Type:**

**Sawafuji SF1000** - PMA + INVERTOR - brushless

Nominal voltage:	1~230V
Frequency:	50 Hz
Protection degree:	IP23

**Version:**

- 1 Socket 230V - 16A
- Automatic voltage regulator
- 12V DC Battery Charger
- Dual speed with economy switch
- Membrane fuel pump
- Oil guard
- Portable
- Recoil starter
- Thermal magnetic breaker

***POWERED by***  
**HONDA™**

SAW  FUJI