

EPSi2000



silenced INVERTER generating sets with HONDA air-cooled petrol engine, 50Hz, 4 stroke

Generator:

kVA max.:	1.7
kVA cont.:	1.5
Amps cont.:	6.4A at 1~230V
Dimensions l x w x h:	56 x 34 x 42 cm
Dry weight:	22 kg

Engine:

Brand/Type:

Honda GX100

HP:	2.8
Power:	2.1 kW (4500 rpm), 1-cylinder Unleaded gasoline, Air-Cooled
Displacement:	98 cm ³
Consumption @75% load:	1.1 litres/hour
Tank:	7.7 litres
Autonomy @75% load:	7 hours
Noise level:	68 dB(A)@7m = Lwa 93

Alternator:

Brand/Type:

Sawafuji SF2000 - PMA + INVERTOR - brushless

Nominal voltage:	1~230V
Frequency:	50 Hz
Protection degree:	IP23

Version:

- 2 Sockets 230V - 16A
- Automatic voltage regulator
- 12V DC Battery Charger
- Membrane fuel pump
- Oil guard
- Portable
- Recoil starter
- Thermal magnetic breaker

W

POWERED by
HONDA™

SAW  **FUJI**